

Yealink VCM35 Pro Datasheet

Yealink VCM35 Pro Datasheet

Introduction

The Yealink VCM35 Pro is an innovative video conferencing microphone designed to accommodate various meeting room needs. The VCM35 Pro features a built-in 6+1 microphone array with an optimal voice pickup radius of 3 m and 360° voice pickup coverage. It supports 360° omnidirectional voice pickup and auxiliary voice localization*.

Equipped with Yealink's high-quality acoustic echo cancellation and noise suppression technologies, the VCM35 Pro can effectively eliminate up to 90 dB of ambient noise, delivering high-quality audio in full-duplex calls. Its advanced voice pickup technology provides comprehensive audio coverage for meeting rooms of all sizes.

The VCM35 Pro is equipped with two VCH ports that support daisy-chain deployment. It supports multiple installation methods, including tabletop placement, adhesive mounting, and in-table embedded installation. With high scalability and flexibility, it enables fast and convenient deployment to fully cover meeting rooms of various sizes.



HD Hi-Fi Microphone



Yealink Full Duplex Technology



3m-360° Voice Pickup Range



Star-Cascaded or Daisy-Chain Deployment



Key Features and Benefits

- HD Hi-Fi microphone
- Yealink full-duplex technology
- 3m radius optimal voice pickup range
- Multiple deployment options
- Daisy-chain support

*Supported in future versions.

Specifications

Specifications	Description
Microphone Features	• HD Audio • Yealink Full Duplex Technology • Yealink Acoustic Echo Canceling • Yealink Noise Proof Technology • 3m radius optimal voice pickup range • Muting the microphone with the touchpad • Auxiliary sound source localization* • Can be used as an expansion microphone • Frequency response: 100Hz to 20kHz
Physical Features	• Dimension (WDH): 110 x 110 x 18 mm • N.W/CTN: 0.261kg • G.W/CTN: 0.306kg • Operating humidity: 10% - 90% • Storage temperature: 0°C - 40°C (+32°F - 104°F)
Package Contents	• VCM35 Pro • RJ45 connector for Ethernet cable • Cable cover • Cable cover screw • Base adhesive • Quick Start Guide

LED Indicator

LED Status	Description
Off	Powered off
Solid green	The audio can be picked up normally during the meeting
Solid red	Muted
Solid yellow	Not selected
Flash yellow	Updating
Flash red	Network connection error.
Flash green	Incoming call

Mute/Unmute Microphone

1. Press the **Mute** button to mute the microphone. The mute LED indicator turns red.
2. Press the **Mute** button again to unmute the microphone.
3. When the device is in standby mode, the mute LED indicator is off.
4. When the device is on a call/in a meeting, the mute LED indicator turns green.